

Vdc		0201	0402	0603	0805	1206	1210	1808	1812	1825	2220	2225
6.3v	NPO											
	X7R			2.2uF	4.7uF							
	X5R	100nF	1uF	10uF	22uF	47uF	100uF					
10V	NPO											
	X7R		100nF	2.2F	4.7uF	10uF	10uF					
	X5R		1uF	4.7uF	10uF	22uF	22uF					
16V	NPO			3.3nF	10nF	27nF	47nF		120nF			
	X7R		100nF	2.2uF	2.2uF	4.7uF	22uF					
	X5R		100nF	2.2uF	10uF	22uF	22uF					
25V	NPO			3.3nF	10nF	10nF	22nF		47nF			
	X7R		10nF	1uF	1uF	2.2uF	10uF					
	X5R		100nF	1uF	4.7uF	10uF	10uF					
35V	NPO											
	X7R				470nF	1uF	4.7uF		2.2uF		10uF	
	X5R					1uF	10uF					
50V	NPO		470pF	3.3nF	10nF	10nF	22nF		47nF			82nF
	X7R		10nF	100nF	330nF	1uF	2.2uF		4.7uF	4.7uF	10uF	6.8uF
	X5R					1uF						
100V	NPO			270pF	1.2nF	6.8nF	10nF		18nF	56nF	56nF	68nF
	X7R			18nF	100nF	470nF	2.2uF		2.2uF	2.2uF	4.7uF	4.7uF
	X5R											
200V	NPO			270pF	1.2nF	5.6nF	8.2nF		12nF	47nF	47nF	56nF
	X7R				47nF	100nF	470nF		1uF	1.5uF	2.2uF	2.2uF
	X5R											
250V	NPO			270pF	1.2nF	5.6nF	8.2nF		12nF	47nF	47nF	56nF
	X7R				47nF	100nF	470nF		1uF	1.5uF	2.2uF	2.2uF
	X5R											
500V	NPO				680pF	2.2nF	3.9nF	1.8nF	8.2nF	39nF	39nF	47nF
	X7R				22nF	56nF	100nF	39nF	220nF	270nF	470nF	470nF
	X5R											
630V	NPO					2.2nF	3.9nF	1.8nF	8.2nF	27nF	27nF	33nF
	X7R					33nF						
	X5R											
1KV	NPO					1nF	1nF	1.2nF	6.8nF	12nF	12nF	15nF
	X7R				1nF	10nF	27nF	15nF	47nF	100nF	100nF	100nF
	X5R											
2KV	NPO					390pF		680pF	1.2nF			
	X7R					1.5nF	2.7nF	3.3nF	10nF	18nF	18nF	18nF
	X5R											
3KV	NPO					39pF		1nF	1.2nF		1.2nF	
	X7R							1.8nF	2.7nF			
	X5R											
4KV	NPO											
	X7R							1nF				
	X5R											
5KV	NPO							27pF			150pF	
	X7R											
	X5R											

Sinus Electronic GmbH

07132 9969 25

Michael.Feimer@sinus-electronic.de